

9002/00-280-186-001 Art. No. 158845



- For the intrinsically safe operation of a wide range of devices, such as HART transmitters, solenoid valves, sensors, potential-free contacts and many more
- Compact and space-saving devices that are easy to install on a DIN rail
- Quick to install as barriers can be simultaneously snapped onto the rail and connected to PE

MY R. STAHL 9002A



The series 9002 INTRINSPAK dual-channel safety barriers enable the intrinsically safe operation of virtually all field devices. The comprehensive portfolio and the combination of safety barriers cover a wide variety of signals. The devices are incredibly robust and require very little space. The back-up fuse is a convenient feature as it is standardised for all variants.

Technical Data

Explosion Protection	
Application range (zones)	2
Ex interface zone	0, 1, 2, 20, 21, 22
IECEEx gas certificate	IECEEx PTB 08.0057X
IECEEx gas explosion protection	Ex ec [ia Ga] IIC T4 Gc
IECEEx dust certificate	IECEEx PTB 08.0057X
IECEEx dust explosion protection	[Ex ia Da] IIIC
ATEX gas certificate	PTB 01 ATEX 2053 X
ATEX gas explosion protection	II 3 (1) G Ex ec [ia Ga] IIC T4 Gc
ATEX dust certificate	PTB 01 ATEX 2053 X
ATEX dust explosion protection	II (1) D [Ex ia Da] IIIC
FMus certificate	3010778
Marking FMus	NONINCENDIVE FOR, Class I, Div. 2, Groups A,B,C,D; T4; Class I, Zone 2, Group IIC T4 IS connections for Class I,II,III, Div. 1, Groups C,D,F,G; Class I, Zone 0, Group IIB Hazardous location when inst. per doc. 90 026 11 31 1
Certificate ULus	E81680V1S3
Marking ULus	For use in Hazardous location, Class I, Div. 2, Groups A,B,C,D; T4 Providing IS circuits for Class I,II,III, GROUPS C,D,E,F,G; per doc. 90 026 11 31 3
cCSA certificate	1284580
Marking cCSA	Associated equipment [Ex ia], Class I, Div. 2, Groups A,B,C,D; Provides IS circuits for Class I,II,III, Class I, Zone 0, Group IIB For applicable grps per inst. doc. 90 026 11 31 2
Inmetro gas certificate	UL-BR 12.0354
Inmetro dust certificate	UL-BR 12.0354

9002/00-280-186-001 Art. No. 158845

Explosion Protection	
Certificates	ATEX (PTB), Brazil (ULB), Canada (CSA), Canada (FM), China (CQST), IECEx (PTB), India (PESO), Japan (CML), Korea (KGS), USA (FM), USA (UL)
Declaration of Conformity	ATEX (EUK), China (CCC)
Installation	in Zone 2, Division 2 and in safe areas
Further information	See relevant certificate and operating instructions

Safety Data					
Max. voltage U _o			28 V		
Max. current I _o			93 mA		
Max. power P _o			650 mW		
Max. permissible external capacity C _o for IIC			0.083 µF		
Max. permissible external inductance L _o for IIC			2 mH		
Max. permissible external capacity C _o for IIB			0.65 µF		
Max. permissible external inductance L _o for IIB			13 mH		
Intrinsically safe limiting values Inductance L _o /capacitance C _o			Jointly connectable inductance L _o /capacitance C _o		
Channel 1	IIC	L _o [mH]		1 mH	0.100 mH
		C _o [µF]		0.0520 µF	0.0830 µF
	IIB	L _o [mH]	10 mH	1 mH	0.1 mH
		C _o [µF]	0.25 µF	0.35 µF	0.65 µF
Channel 2	IIC	L _o [mH]		1 mH	0.1 mH
		C _o [µF]		0.052 µF	0.083 µF
	IIB	L _o [mH]	10 mH	1 mH	0.1 mH
		C _o [µF]	0.25 µF	0.35 µF	0.65 µF
Channels 1 + 2	IIC	L _o [mH]			
		C _o [µF]			
	IIB	L _o [mH]		1 mH	0.1 mH
		C _o [µF]		0.34 µF	0.551 µF

Electrical Data							
Number of channels		2					
Maximum resistance R_{max}		359 Ω					
Minimum resistance R_{min}		322 Ω					
Maximum output current I_{max}		69 mA					
Potential channel 1		Negative					
Potential channel 2		Negative					
Transmission frequency channel 1		≤ 100 kHz					
Type of voltage		DC					
I_{leak} leakage current for U_n		≤ 2 μ A					
Chan-nel	Nominal volt-age U_n	Maximum output current I_{max}	Minimum resist-ance R_{min}	Maximum resist-ance R_{max}	Maximum voltage U_o	Maximum current I_o	Maximum power P_o
1	25.00 V DC	69 mA	322 Ω	359 Ω	28 V	93 mA	650 mW
2	25 V	69 mA	322 Ω	359 Ω	28 V	93 mA	650 mW
1 + 2					28 V	186 mA	1300 mW


Safety barriers
Dual-channel safety barrier



9002/00-280-186-001 Art. No. 158845

Table with technical specifications categorized into Auxiliary Power, Output, Ambient Conditions, Mechanical Data, and Mounting / Installation. It includes details like power supply, temperature influence, ambient temperature ranges, degree of protection (IP), enclosure material, connection details, dimensions, and torque requirements.


Technical Drawings – Subject to Alterations






Dual-channel safety barriers, potential: - / -

9002/00-280-186-001 Art. No. 158845


Dimensional Drawings (All Dimensions in mm [inches]) – Subject to Alterations



Accessories

Terminal block		Art. No.
	Phoenix Contact terminal block UT 4-PE	113057
	Phoenix Contact terminal block UT 6-PE	113058
Adaptor		Art. No.
	The adaptor enables a series 900x safety barrier to be installed on a mounting plate from a previous series.	158826
Clamping base, moulded material		Art. No.
	Enables the safety barrier to be mounted on a G-rail.	165283
Fuse holder		Art. No.
	The fuse holder is snapped onto the side of a safety barrier and can be equipped with up to five back-up fuses (replacement).	158834
Spare Parts		
Back-up fuse		Art. No.
	For all series 9001, 9002 and 9004 safety barriers Packaging unit: 5 pieces	158964

9002/00-280-186-001 Art. No. 158845

Label carrier		Art. No.
	Transparent cover for the label	158977

We reserve the right to make alterations to the technical data, dimensions, weights, designs and products available without notice. The illustrations cannot be considered binding.